



# Stephen P. Wales Ltd

The Old Brewery Works, Lr Ellacombe Church Rd,  
Torquay. UK. TQ1 1JH  
Tel: 01803 295430 Fax: 01803 212819  
email: sales@stephenwales.co.uk

## TIM-30 Coin timer



### Coinage options: (side entry only)

single coin: 20p, £1, €1, 50cents, token  
Dual coin £1 and 20p, or £1 and 10p



### Override keyswitch

Fitted as Standard

### Large LED Display

Counts down in hours, minutes or seconds

### Programmable

When the cash-box is removed the front buttons automatically go into programming mode

### Strong

Reinforced, High impact ABS.  
The cash box bolts through to the back for added strength.

### Pre-end audible alarm

1 minute before switch-off

**Coin counter 1** Counts how much should be in the cash box

**Coin Counter 2** Counts how much entered since new.

**Suitability** Showers, Washing machines, Tumble driers, Snooker lights, squash lights, Hair driers, Irons, Pressure washers, internet or PC time control, TV time control, Gaming modules TV control, Any timed lighting e.g. outdoor football pitches, tennis, equestrian lighting.

### Installation

Instructions and operating sheet provided with the unit  
Fix to vertical surface only.  
Fixings for hard wall or cavity wall supplied with the unit.

### Electrical

3 terminals:  
Live in - Neutral in/out - Live out  
An additional earth bypass connector provided.  
Connectors take 10mm<sup>2</sup> (4mm diameter) cable  
Knockout on the bottom of unit

### Keys

One set of 3 keys (override, front case and cash box) provided with the unit

### SPECIFICATION

#### Dimensions

Height 270mm (10<sup>3</sup>/<sub>4</sub>"  
Width 183mm (7<sup>1</sup>/<sub>4</sub>"  
Depth 93mm (3<sup>3</sup>/<sub>4</sub>"

**Weight** 1.4kg

**Case** High impact ABS

**Voltage** 230v. only

**Amperage** 30amp maximum  
(Higher currents require a contactor)

**Power consumption** 22w max.

**Standards** BSEN 30730-1:1992  
& part 2.7 of that  
standard 1989 EMC  
directive

**General Standards** EN50081-1  
EN50082-1

**Waterproof** No IP rating